

BUS EQUIPMENT LIST

FOR INFO

		NORM			EMER ELEC		
		AC	DC	DC BAT	AC ESS	DC ESS	HOT
ADIRU	ADIRU 1				X		HOT 1 (1)
	AOA RESOLVER 1				X (2)		
	ADIRU 2	AC2-3					HOT 2 (1) during 5 mn
	AOA RESOLVER 2	AC2-3					
	ADIRU 3	AC1-3			X (3)		HOT 2 (1)
	AOA RESOLVER 3	AC1-2			X (2)		
STD BY INST	HORIZON					X	
	ALTIMETER					SHED	
	DDRMI				X		
	COMPASS					X	
NAVAIDS	VOR 1				X		
	VOR 2	AC2-3					
	MMR 1				X		
	MMR 2	AC2-3					
	ADF 1				X		
	ADF 2	AC2-3					
	DME 1	AC1-1					
	DME 2	AC2-3					
RADIO ALTIMETER	RA 1	AC1-2					
	RA 2	AC2-3					
ATC	ATC 1				X		
	ATC 2	AC2-3					
GPWS		AC1-2					
WEATHER RADAR	WX 1	AC1-2					
	WX 2	AC2-3					
TCAS		AC1-1					
HUD		AC1	DC1				
PVI		AC1-1					

(1) Back up supply

(2) AOA1 resolver power supply is lost and AOA3 resolver power supply is recovered when AC1-2 lost and AIR DATA CAPT ON 3 selected.

(3) When AC1-2 lost.